

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - LETTER

Lexmark MS810de

Testing Incomplete. Non-Clearable 31.21 Error on 2 devices. Testing will complete and a new report published when the devices are repaired.

Printing device and settings

Test Start Date and Time	1/14/2015 10:37
Tester	KN
Machine name/model	MS810de
Colour or B&W	B&W
FW Version	NA
Temperature and Humidity	75 degF / 24 degC, 20 %rH
Voltage	110V
Test End Date and Time	1/15/2015 11:09

Item	Value	
Mode and Setting	Driver Version	NA
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	NA
	Duplex B&W Settings	NA
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Colorlok / Xerox Business 4200

Summary Report: Letter

Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	9.3	54.9
	Duplex	10.9	36.0

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: LETTER

Office Category Test	FSOT (secs)	EFTP (ipm)				ESAT (ipm)
		1 set only (1 set)	1 set only (1 set)	1 set + 30sec (# of sets)	1 set + 4min (# of sets)	
Color Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode (optional for color device)	Simplex - Adobe Reader	9.16	26.19 (1 set)	48.74 (9 sets)	N/A	54.96
	Simplex - Word	9.16	26.17 (1 set)	49.02 (9 sets)		55.01
	Simplex - Excel	9.35	25.66 (1 set)	48.87 (9 sets)		55.02
	Simplex - Average	9.3	26.0	48.8	N/A	54.9
	Duplex - Adobe Reader	10.82	18.98 (1 set)	30.30 (6 sets)		36.06
	Duplex - Word	10.91	18.84 (1 set)	30.20 (6 sets)		36.04
	Duplex - Excel	10.70	19.16 (1 set)	30.38 (6 sets)		36.10
	Duplex - Average	10.9	18.9	30.2		36.0

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters

Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 -3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCSHR ATA
I/O Subsystem	Builtin
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - A4

Lexmark MS810de

Testing Incomplete. Non-Clearable 31.21 Error on 2 devices. Testing will complete and a new report published when the devices are repaired.

Printing device and settings

Test Start Date and Time	1/14/2015 10:37
Tester	KN
Machine name/model	MS810de
Colour or B&W	B&W
FW Version	NA
Temperature and Humidity	75 degF / 24 degC, 20 %rH
Voltage	110V
Test End Date and Time	1/15/2015 11:09

Item	Value	
Mode and Setting	Driver Version	NA
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	NA
	Duplex B&W Settings	NA
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Colorlok / Xerox Business 4200

Summary Report: A4

Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	9.4	52.0
	Duplex	11.0	34.4

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: A4

	Office Category Test	FSOT (secs)	EFTP (ipm)			ESAT (ipm)
		1 set only (1 set)	1 set only (1 set)	1 set + 30sec (# of sets)	1 set + 4min (# of sets)	1 set + 30sec
Colour Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode <small>(optional for color device)</small>	Simplex - Adobe Reader	9.31	25.78 (1 set)	46.02 (8 sets)	N/A	52.14
	Simplex - Word	9.35	25.66 (1 set)	46.11 (8 sets)		52.10
	Simplex - Excel	9.53	25.15 (1 set)	45.94 (8 sets)		52.05
	Simplex - Average	9.4	25.5	46.0	N/A	52.0
	Duplex - Adobe Reader	10.98	18.84 (1 set)	29.10 (6 sets)		34.47
	Duplex - Word	11.02	18.78 (1 set)	29.04 (6 sets)		34.46
	Duplex - Excel	10.95	18.89 (1 set)	29.22 (6 sets)		34.56
	Duplex - Average	11.0	18.8	29.1		34.4

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters

Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 -3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCASHR ATA
I/O Subsystem	BuiltIn
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - LETTER

Lexmark MS810de

Printing device and settings	
Test Start Date and Time	1/14/2015 10:37
Tester	KN
Machine name/model	MS810de
Colour or B&W	B&W
Configuration (options)	Default
Controller	Not Specified
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	76 degF / 24 degC, 18 %rH
Voltage	110V
Test End Date and Time	1/15/2015 16:37

Item	Value
Mode and Setting	
PDL and driver version	default
Print Quality mode	default
B&W settings	default
Paper feed orientation	Short Edge
Paper	
Paper type setting	default
Paper feeding	Standard cassette
Paper Path	
Paper exit	Standard exit tray
Output orientation	default (face up or face down)
Duplexing unit	Short Edge

ISO First Page Out Time Summary Report: Office Category

Summary Report: Letter		F POT from Ready (seconds)
B&W	Simplex	5.8
	Duplex	10.0

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.
 5) Page counts were collected after completion of the tests.

ISO First Page Out Time Report: Office Category

Detailed Report: LETTER						
		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Color Mode	F POT from Ready - Simplex					
	F POT from Ready - Duplex					
	F POT from Sleep - Simplex					
	Recovery Time					
	F POT from Off - Simplex					
	Warm-up Time					
B&W Mode	F POT from Ready - Simplex	5.76	5.90	5.61	5.76	50 Seconds
	F POT from Ready - Duplex	9.88	10.11	9.93	9.98	50 Seconds
	F POT from Sleep - Simplex			10.73		
	Recovery Time			5.1		
	F POT from Off - Simplex			81.56		
	Warm-up Time			75.95		

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.
 5) Page counts were collected after completion of the tests.

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aC5HR ATA
	I/O Subsystem	Builtin
	USB Subsystem	USB 2.0/3.0
Printing Device Connection	TCP/IP	10/1000
Software	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
	Printing Applications	Microsoft Office 2010 SP2
	Print Driver	Adobe Reader 10.1.4
	Test files and location	NA
		Office category files, hard drive

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - A4

Lexmark MS810de

Printing device and settings	
Test Start Date and Time	1/14/2015 10:37
Tester	KN
Machine name/model	MS810de
Colour or B&W	B&W
Configuration (options)	Default
Controller	Not Specified
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	76 degF / 24 degC, 18 %rH
Voltage	110V
Test End Date and Time	1/15/2015 16:37

Item	Value	
Mode and Setting	PDL and driver version	default
	Print Quality mode	default
	B&W settings	default
	Paper feed orientation	Short Edge
Paper	Paper type setting	default
	Paper feeding	Standard cassette
	Paper exit	Standard exit tray
Paper Path	Output orientation	default (face up or face down)
	Duplexing unit	Short Edge

ISO First Page Out Time Summary Report: Office Category		
Summary Report: A4		
		F POT from Ready (seconds)
B&W	Simplex	5.8
	Duplex	10.2
Notes		
1) All printing device and driver settings were default mode.		
2) For the B/W results, the print driver was set to "print in B/W".		
3) For more information see http://www.hp.com/go/printerclaims .		
4) Port monitor not configured to follow device if the IP address changes.		
5) Page counts were collected after completion of the tests.		

ISO First Page Out Time Report: Office Category						
Detailed Report: A4						
		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Colour Mode	F POT from Ready - Simplex					
	F POT from Ready - Duplex					
	F POT from Sleep - Simplex					
	Recovery Time					
	F POT from Off - Simplex					
	Warm-up Time					
B&W Mode	F POT from Ready - Simplex	5.68	5.95	5.79	5.81	50 Seconds
	F POT from Ready - Duplex	9.93	10.18	10.36	10.16	50 Seconds
	F POT from Sleep - Simplex			10.72		
	Recovery Time			4.9		
	F POT from Off - Simplex			82.36		
	Warm-up Time			76.56		
Notes						
1) All printing device and driver settings were default mode.						
2) For the B/W results, the print driver was set to "print in B/W".						
3) For more information see http://www.hp.com/go/printerclaims .						
4) Port monitor not configured to follow device if the IP address changes.						
5) Page counts were collected after completion of the tests.						

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aCSHR ATA
	I/O Subsystem	Builtin
	USB Subsystem	USB 2.0/3.0
Printing Device Connection	TCP/IP	10/1000
Software	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
	Printing Applications	Microsoft Office 2010 SP2
		Adobe Reader 10.1.4
	Print Driver	NA
	Test files and location	Office category files, hard drive