



HP LaserJet Managed Flow MFP M830zm

HP Managed MFPs and printers are optimized for managed environments. Offering increased monthly page volumes and fewer interventions, this portfolio of products can help reduce printing and copying costs. See your HP Authorized Reseller for details.



Give workgroups the speed they need

- Let departments scan without worry. HP EveryPage detects potential errors or missed pages on the spot.
- Create easily searchable scanned files, using built-in optical character recognition software.
- Simplicity all around—make it easy for all to print with one common driver.⁴
- Forget email—easily scan and send documents to Microsoft® SharePoint® in one step.

Keep business moving

- Save on both sides—capture documents faster with two-sided, single-pass scanning.
- Add finishing touches faster—let employees bind big jobs faster using the built-in finishing options.⁷
- Don't wait—print right away with Instant-on Technology.
- Make it easy to be efficient, with an intuitive touchscreen and keyboard for entering file information.

Mobile printing—more efficient

- Mobile printing at a touch—enable touch-to-print convenience from mobile devices.²
- Simplify printing. Give users simple, direct access to the MFP through wireless direct printing.¹
- Let employees print from mobile devices with built-in print capability or HP ePrint app and software.⁵
- Printing made Apple® simple—let employees print wirelessly from an iPad®, iPhone®, or iPod touch®.⁶

Invest once, expand easily and manage efficiently

- Expand your options. Easily upgrade firmware on your schedule. Easily integrate solutions or devices at will.
- Help build business efficiency. Centrally monitor and control printers with HP Web Jetadmin.⁸
- Apply fleet-wide policies to help protect all your HP devices with the HP Imaging and Printing Center.³
- Confidently safeguard the sensitive data sent to your MFP with the HP High-Performance Secure Hard Disk.



¹Wireless direct printing may be added as an option to the HP LaserJet Managed Flow MFP M830zm L3U65A. Mobile device may require an app or driver. Wireless performance is dependent on physical environment and distance from the printer. For details, see hp.com/go/wirelessprinting. ²Touch-to-print capability may be added as an option to the HP LaserJet Managed Flow MFP M830zm L3U65A. Mobile device must support near field communications-enabled printing. For a list of supported devices, see hp.com/go/mobileprinting. ³HP Imaging and Printing Security Center must be purchased separately. ⁴The HP Universal Print Driver is free and available for download at hp.com/upd. ⁵Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to printer. Wireless performance is dependent upon physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an internet connection to a HP Web-connected printer. App or software may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See hp.com/go/mobileprinting for more details. ⁶Supports OS X® Lion, OS X Mountain Lion, and the following devices running iOS 4.2 or later: iPad® (all models), iPhone® (3GS or later), and iPod touch® (third generation or later). Works with HP's AirPrint-enabled printers and requires the printer be connected to the same network as your OS X or iOS device. Wireless performance is dependent on physical environment and distance from the access point. OS X, iPad, iPhone, and iPod touch are trademarks of Apple® Inc., registered in the United States and other countries. AirPrint™ and the AirPrint logo are trademarks of Apple Inc. ⁷Paper-handling options depend on the output configuration selected at time of purchase. ⁸HP Web Jetadmin is free and available for download at hp.com/webjetadmin

HP LaserJet Managed Flow MFP M830zm Specifications Table

| | |
|---|---|
| Functions / Multitasking Supported | Print, copy, scan, fax / Yes |
| Print Speed | Letter: Up to 55 ppm black; First Page Out: As fast as 9.5 sec black |
| Print Resolution | Black (best): Up to 1200 x 1200 dpi |
| Print Technology | Laser |
| Print Resolution Technologies | HP ProRes 1200 (1200 x 1200 dpi), HP FastRes 1200 (1200 dpi quality), HP Resolution Enhancement technology, 600 x 600 dpi, 300 x 300 dpi |
| Print Cartridges Number | 1 (black) |
| Standard Print languages | HP PCL 6, HP PCL 5, HP postscript level 3 emulation, native PDF printing (v.1.4) |
| Printer Smart Software Features | HP ePrint, Apple AirPrint™, Mopria-certified, Open Extensibility Platform, FutureSmart Firmware, Instant-on Technology, HP Auto-On/Off technology, HP Easy Color, HP print preview, duplex, print multiple pages per sheet (2, 4, 6, 9, 16), collation, watermarks, store print jobs, job separator, staple, offset, booklet making, hole punch |
| Printer Management | HP Web Jetadmin; HP Utility (Mac) |
| Scan Type / Technology | Flatbed, ADF / Contact Image Scanner (CIS) |
| Scan Resolution | Hardware: Up to 300 x 600 dpi (ADF); Up to 600 x 600 dpi (flatbed); Optical: Up to 600 dpi |
| Scan File Format | Digital Send: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Scan to easy access USB: PDF, JPEG, TIFF, MTIFF, XPS, PDF/A, TEXT (OCR), Unicode TEXT (OCR), RTF (OCR), Searchable PDF (OCR), Searchable PDF/A (OCR), HTML (OCR), CSV (OCR); Print from easy access USB: PDF, PS, Print Ready files (.prr, .pml, .cht) |
| Scan Input Modes | Front-panel scan, copy, fax, email |
| Scan Size | ADF: 11.7 x 17 in Maximum; 2.7 x 5 in Minimum; Flatbed: 11.7 x 17 in |
| Scan Speed | Up to 70 ppm (B&W), up to 68 ppm (color)/ Duplex: Up to 85 ipm (B&W), up to 63 ipm (color) |
| Scanner Advanced Features | Optimize text/picture; Image adjustments; Job build; Output quality setting; Selectable scan resolution 75 to 600 dpi; Auto detect color; Edge erase; Auto tone; Auto job notification; Blank page suppression; Auto orientation; Auto page crop; HP Quick Sets |
| Bit depth / Grayscale levels | 24-bit / 256 |
| Digital Sending Standard Features | Scan to e-mail; Save-to-Network Folder; Scan to SharePoint; Save-to-USB driver; Send to FTP; Send to LAN Fax; Send to Internet Fax; Local Address Book; SMTP over SSL |
| Copy Speed | Black (letter): Up to 55 cpm |
| Copy Resolution | Black (text and graphics): Up to 600 x 600 dpi; Up to 600 x 600 dpi; Color (text and graphics): Up to 600 x 600 dpi |
| Maximum Number Of Copies | Up to 999 copies |
| Copier Resize | 25 to 400% |
| Copier Settings | Image adjustment (Darkness, Contrast, Background Cleanup, Sharpness); Reduce/Enlarge; Auto-Scaling; N-up; Multi-Feed Detector; Job Build; Auto-Size Detection; Edge-to-Edge; 2-sided ID Scan; Optimize Text/Picture; Book Mode; One-Pass Duplex; Change Size; Change Orientation |
| Fax Speed | Up to: 33.6 kbps; Letter: 3 sec per page |
| Fax Resolution | Black (best): Up to 300 x 300 dpi; Black (standard): 200 x 100 dpi |
| Fax Smart Software Features | Stored faxes; fax archiving; fax forwarding; scale-to-fit; fax address book; LAN/Internet fax; fax number confirmation; Holiday fax schedule |
| Fax Features | Fax Memory: Up to 500 pages; Auto Fax Reduction Supported: Yes; Auto-Redialing: Yes; Fax Delayed Sending: No; Distinctive Ring Detection Supported: No; Fax Forwarding Supported: Yes; Fax Phone TAMI Interface Supported: No; Fax Polling Supported: No; Fax Poll to receive only: Fax Telephone Mode Supported: No; Junk Barrier Supported: Yes; Maximum Speed Dialing Numbers: Up to 100 numbers; PC Interface Supported: Yes; Remote Retrieval Capability Supported: No; Telephone Handset Supported: No |
| Standard Connectivity | 2 Hi-Speed USB 2.0 Host; 1 Hi-Speed USB 2.0 Device; 1 Gigabit Ethernet 10/100/1000T network; 1 FireWire Interface; 1 Hardware Integration Pocket; 2 Internal USB Host |
| Network Capabilities | Ethernet; Fast Ethernet; 802.3/802.3u; RJ-45 (10/100/1000Base-TX); Optional NFC/Wireless |
| Network Ready | Standard (built-in Ethernet) |
| Wireless Capability | Optional, enabled with purchase of a hardware accessory |
| Mobile Printing Capability | HP ePrint, Apple AirPrint™, Mopria-certified, Mobile Apps, Wireless Direct printing (optional) |
| Memory | Standard: 1.5 GB; Maximum: 1.5 GB |
| Processor Speed | 800 MHz / Hard disk: 320 GB |
| Duty Cycle | Monthly, letter: Up to 450,000 pages |
| Recommended Monthly Page Volume | 15,000 to 100,000 |
| Media Types Supported | Paper (bond, color, letterhead, plain, preprinted, prepunched, recycled, rough), labels, cardstock, transparencies |
| Media Weight Supported | Tray 1: 16 to 58 lb (bond); Tray 2/3: 16 to 53 lb (bond); High-capacity Input tray: 16 to 53 lb (bond) |
| Media Sizes Supported | Tray 1: Letter, legal, executive, 11 x 17, 12 x 18, 8.5 x 13; envelopes (No. 10); Tray 2, 3: letter, legal, executive, 11 x 17, 8.5 x 13; High-capacity Input tray: letter |
| Media Sizes Custom | Tray 1: 3.86 x 7.52 to 12.28 x 18.5 in; Tray 2, 3: 5.83 x 8.27 to 11.69 x 17.0 in; High-capacity Input tray: 8.5 x 11 in |
| Paper Handling | Two 500-sheet input trays, 100-sheet multi-purpose tray, 3500-sheet High-capacity tray; Up to 3000 sheets (with optional stapler/stapler, stapler/stapler with hole punch, or stapler/stapler with booklet maker); Duplex Options: Automatic (standard); Auto Document Feeder Capacity: Standard, 200 sheets (20 lb; 22 mm); Envelope Feeder: No; Standard Paper Trays: 5; Input Capacities: Up to 4600 sheets; Output Capacities: Up to 3000 sheets (with optional stapler/stapler, stapler/stapler with hole punch, or stapler/stapler with booklet maker); Up to 50 envelopes (No. 10); Up to 100 sheets |
| What's in the box | L3U65A HP LaserJet Managed M830zm Multifunction Printer; Black print cartridge; keyboard overlay; CD(s) with software and documentation; Getting Started Guide; Power cord; Choice of output paper handling device (Printer must be ordered with one of four paper output accessories) |
| Replacement Cartridges | HP CF325XC High Yield Black Contract Original LaserJet Toner Cartridge (~ 42,600 pages) CF325XC |
| Product Dimensions | W x D x H: 65 x 28.1 x 43.3 in; Maximum: 77.7 x 28.1 x 43.3 in |
| Product Weight | 449.7 lb (with stapler/stapler hole punch), 491.6 lb (with booklet maker) |
| Warranty Features | One-year, onsite limited warranty; 24-hour support; 7 days a week phone support |
| Energy Efficiency Compliance | ENERGY STAR® qualified; EPEAT® Silver |

| | |
|---|--|
| Control Panel | 8.0-in (20.3 cm) color LCD with Capacitive touchscreen; rotating (adjustable angle) display; illuminated Capacitive Home button (for quick return to the Home menu); Easy Access USB; Hardware Integration Pocket |
| Display Description | 8.0" (20.3 cm), SVGA LCD (color graphics) |
| Software Included | HP PCL 6 Discrete Printer Driver; Mac SW Link to Web (Mac Installer), Windows Installer |
| Fonts and Typefaces | 105 internal TrueType fonts scalable in HP PCL; 92 internal scalable fonts in HP Postscript Level 3 emulation (Euro symbol built-in); 1 internal Unicode font (Andale Mono WorldType); 2 Internal Windows Vista 8 Fonts (Calibri, Cambria); additional font solutions available via third-party flash memory cards; HP LaserJet Fonts and IPDS Emulation available at hp.com/go/laserjetfonts |
| Compatible Operating Systems | Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (SP2 or higher) (32-bit/64-bit), Windows Server 2012 (64-bit), Windows Server 2008 (32-bit/64-bit), Windows Server 2008 R2 (64-bit), Windows Server 2003 (SP1 or higher) (32-bit/64-bit), Windows XP x64 OS version 10.6.8, 10.7.5 Lion, 10.8 Mountain Lion. For the latest operating system support see: Air Print (support.apple.com/kb/ht4356); Android (android.com/); Citrix and Windows Terminal Services (hp.com/go/udp); HP ePrint Software Driver (hp.com/go/eprintssoftware); Linux (hplip.net); Novell (novell.com/irprint); SAP device types (hp.com/go/sap/drivers); SAP Print (hp.com/go/sap/print); UNIX (hp.com/go/UNIX); UNIX JetDirect (hp.com/go/jetdirectunix_software) |
| Compatible Network Operating Systems | Windows 8.1 (32-bit/64-bit); Windows 8 Basic (32-bit/64-bit); Windows 8 Pro (32-bit/64-bit); Windows 8 Enterprise (32-bit/64-bit); Windows 8 Enterprise H (32-bit/64-bit); Windows 8 Enterprise RT (32-bit only); Windows 7 (32-bit/64-bit) (Including Starter Edition); Windows Vista (32-bit) (Including Starter Edition); Windows Vista (64-bit); Windows XP (SP2 or higher) (32-bit/64-bit); Windows Server 2012 R2; Windows Server 2012 (No Software Installer support); Windows Server Win7/2008 R2 (SP1); Windows Server 2008 (Standard Edition); Windows Server 2008 (Enterprise Edition); Windows Server 2008 (32-bit/64-bit) (SP1); Windows Server 2008 (32-bit/64-bit) (SP2); Windows Server 2008 R2 (32-bit/64-bit) (Standard Edition, Enterprise Edition); Windows Server 2008 Server Terminal Services; Windows Server 2008 Server Terminal Services with Citrix XenApp; Windows Server 2003 (Standard Edition); Windows Server 2003 (Enterprise Edition); Windows Server 2003 (32-bit/64-bit) (SP1); Windows Server 2003 (32-bit/64-bit) (SP2); Windows Server 2003 R2 (32-bit/64-bit) (Standard Edition, Enterprise Edition); Windows Server 2003 Server Terminal Services; Windows Server 2003 Server Terminal Services with Citrix MetaFrame XP with Feature Release 3; Windows Server 2003 Server Terminal Services with Citrix Presentation Server 4.0; Windows Server 2003 Server Terminal Services with Citrix Presentation Server 4.5; Novell NetWare 6.5; Novell NetWare 6.5 SP6 minimum for full Windows Vista, Windows 7 and Windows XP (SP7 only Windows XP); Novell Novell iPrint Client v5.4 for Windows XP; Windows Vista and Windows 7, x86 and x64; Novell Novell iPrint Support Only; Novell Novell Open Enterprise Server 2 (Linux); Novell Novell Open Enterprise Server 6.5; Other Citrix (Print): Citrix XenApp 6.0, Xen Server 5.6, Xen Desktop 5.5; Other Cluster Support; Mac 10.5; Mac 10.6.8; Mac 10.7.5; Mac 10.8.x; Mac 10.9.x; For Linux OS versions, refer to the HP Linux web site: hplipopensource.com/hplip-web/index.html; UNIX HP/UX 11.x; IBM AIX 3.2.5 or higher; MPE-iX; Citrix MetaFrame Server; Red Hat Linux 7.x or higher; Solaris 2.5 or higher (SPARC systems only); SuSE Linux 8.x or higher. (For Microsoft IPv6 compatibility use Windows 2003, Windows XP Home, Windows XP Professional and Windows Vista) |
| Minimum System Requirements | PC: Windows 8; Windows 7 SP1+; Windows Vista; Windows Server 2003 (SP1+); Windows Server 2008; Windows Server 2008 R2 (64-bit); Windows Server 2012 (64-bit); Windows XP (SP2+); CD-ROM or DVD drive, or Internet connection; dedicated universal serial bus (USB 1.1 or 2.0), or network connection; 200 MB available hard disk space; operating system compatible hardware system requirements see microsoft.com; MAC: Mac OS X v10.6.8, OS X 10.7.5 Lion, OS X 10.8 Mountain Lion; 1 GB of available hard-disk space; CD-ROM or DVD drive, or Internet connection; Dedicated universal serial bus (USB 1.1 or 2.0), or network connection (Operating system compatible hardware system requirements see apple.com) |
| Power | Power Supply Type: Built-in power supply; Power Requirements: Input Voltage: 220 to 240 VAC, 50/60 Hz, 5.5 A (Not dual voltage, power supply varies by part number with # Option code identifier); Power Consumption: 1030 watts (Printing), 60 watts (Ready), 6.0 watts (Sleep 1), 2.5 watts (Auto On/Off), 0.3 watts (Off) |
| Acoustics | Acoustic Power Emissions: 7.5 B(A); Acoustic Pressure Emissions: 58 dB(A) |
| Operating Environment | Operating Temperature Range: 50 to 91°F; Recommended Operating Temperature: 50 to 91°F; Storage Temperature Range: 32 to 104°F; Non-Operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating Range: 10 to 80% RH |
| Security Management | Identity Management: Kerberos authentication, LDAP authentication, 1000 user PIN codes, optional HP and 3rd party advanced authentication solutions (e.g., badge readers); Network: IPsec/firewall with Certificate, Pre-Shared Key, and Kerberos authentication, Supports WPA-10 IPsec configuration Plug-in, WPA2-Enterprise, 802.1X authentication (EAP-PEAP, EAP-TLS), SNMPv3, HTTPS, Certificates, Access Control List; Data: Storage Encryption, Encrypted PDF (uses FIPS 140 validated cryptographic libraries from Microsoft), Encrypted Email, Secure Erase, SSL/TLS (HTTPS), Encrypted Credentials Device: Security lock slot, USB port disablement, Hardware Integration Pocket for security solutions; Security Management: Compatible with HP Imaging & Printing Security Center |
| Accessories | HP Stapler Cartridge Refill C8091A, HP 2-pack 2000-Staple Cartridge CC383A, HP LaserJet Stapler/Stacker CZ994A, HP LaserJet Stapler/Stacker with 2/3 Hole Punch CZ995A, HP LaserJet Booklet Maker/Finisher CZ285A, 110v Maintenance Kit CZH67A, 220v Maintenance Kit CZH57A, HP Jetdirect 2700w USB Wireless Print Server J8026A, HP LaserJet ADF Roller Replacement Kit C1P70A, HP Trusted Platform Module Accessory F5562A |
| HP Service and Support Options | HP 2 year Next business day LaserJet M830MFP Hardware Support; HP 3 year Next business day LaserJet M830MFP Hardware Support; HP 3 year Next business day LaserJet M830MFP Hardware Support; HP 4 year Next business day LaserJet M830MFP Hardware Support; HP 5 year Next business day LaserJet M830MFP Hardware Support; HP 3 year 4 hour 9x5 LaserJet M830MFP Hardware Support; HP 3 year 4 hour 13x5 LaserJet M830MFP Hardware Support; HP 4 year 4 hour 9x5 LaserJet M830MFP Hardware Support; HP 4 year 4 hour 13x5 LaserJet M830MFP Hardware Support; HP 5 year 4 hour 9x5 LaserJet M830MFP Hardware Support; HP 5 year 4 hour 13x5 LaserJet M830MFP Hardware Support; HP 3 year Next business day + DMR LaserJet M830MFP Support; HP 4 year Next business day + DMR LaserJet M830MFP Support; HP 5 year Next business day + DMR LaserJet M830MFP Support; HP 1 year Post Warranty Next business day LaserJet M830MFP Support; HP 2 year Post Warranty Next business day LaserJet M830MFP Support; HP 3 year Post Warranty Next business day LaserJet M830MFP Support; HP 4 year Post Warranty Next business day LaserJet M830MFP Support; HP 5 year Post Warranty Next business day LaserJet M830MFP Support; HP 1 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 2 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 3 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 4 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 5 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 1 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 2 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 3 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 4 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support; HP 5 year Post Warranty Next business day + max3 MKRS LaserJet M830MFP Support |

Learn more at hp.com

¹Face-up tray installed, multipurpose tray closed, output device attached with tray extended. ²With print cartridges ³Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. ⁴Average declared yields based on ISO/IEC 19798 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see hp.com/go/learnaboutsupplies ⁵Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit hp.com/go/learnaboutsupplies. Actual yields vary considerably based on images printed and other factors. For details see hp.com/go/learnaboutsupplies ⁶HP ePrint: Requires an Internet connection to the printer. Feature works with any connected Internet- and e-mail-capable device. Requires HP Web Services Account Registration. Print times may vary. For a list of supported documents, and images, see hp.com/go/eprintcenter. HP Wireless Direct printing; Requires purchase of optional HP Jetdirect 2800w USB Wireless Print Server J8029A HP accessory. Apple AirPrint™; Supports the following devices running iOS 4.2 or later: iPad®, iPad®, iPhone® (3GS or later), iPod touch® (3rd generation or later). Works with HP's AirPrint™ enabled printers and requires the printer be connected to the same network as your iOS device. Wireless performance is dependent upon physical environment and distance from the access point. AirPrint, the AirPrint Logo, iPad, iPhone, and iPod touch are trademarks of Apple®, Inc., registered in the U.S. and other countries. Mobile Apps; For additional solutions, see hp.com/go/mobile-printing-solutions ⁷First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see hp.com/go/irprintclaims. Standard ITU-T test image #1 at high resolution and MMR encoding, the HP fax device can transmit at 3 sec/page for V.34 and 6 sec/page for V.17 ⁸Measured using ISO/IEC 24734, excludes first set of test documents. For more information see hp.com/go/irprintclaims. Standard ITU-T test image #1 at high resolution and MMR encoding, the HP fax device can transmit at 3 sec/page for V.34 and 6 sec/page for V.17 ⁹Exact speed varies depending on the system configuration, software application, driver, and document complexity. ¹⁰Acoustic values are subject to change. For current information see hp.com/support ¹¹Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups. ¹²HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. For more information, visit hp.com/go/SureSupply; only available with Original HP supplies; Internet access required ¹³Scan speeds measured from automatic document feeder when scanning to digital file. Actual speeds may vary depending on scan resolution, network conditions, computer performance and application software. ¹⁴Windows Installer has the same Operating System support as the printer driver except the following: Windows XP SP3+ (32-bit only); Windows Server 2003 SP2+ (32-bit only); Windows Vista Starter not supported in Driver not Installer; HP Software Installer CD for Windows. The HP PCL 6 discrete driver and .NET 3.5 SP1 are installed for Windows operating systems along with other optional software. .NET 4.0 is included in Windows 8/Server 2012; HP Software for Mac is no longer included on the CD, but can be downloaded from hp.com – the Mac driver and Mac Utility are installed for Mac operating systems.

© Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.

