

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - LETTER

HP LaserJet Enterprise M506 Series

Printing device and settings	
Test Start Date and Time	6/17/2015 21:53
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Temperature and Humidity	74 degF / 23 degC, 34 %RH
Voltage	110V
Test End Date and Time	6/30/2015 15:47

Item	Value	
Mode and Setting	Driver Version	Release15106_504-231
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	Default
	Duplex B&W Settings	Default
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Ultra White / HP Office

Summary Report: Letter			
Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	9.9	45.9
	Duplex	13.4	37.2

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: LETTER						
	Office Category Test	FSOT (secs) 1 set only (1 set)	EFTP (ipm)			ESAT (ipm) 1 set + 30sec
			1 set only (1 set)	1 set + 30sec (# of sets)	1 set + 4min (# of sets)	
Color Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode (optional for color device)	Simplex - Adobe Reader	10.45	22.96 (1 set)	40.17 (8 sets)	44.84 (50 sets)	45.94
	Simplex - Word	9.47	25.33 (1 set)	41.21 (8 sets)		45.93
	Simplex - Excel	9.58	25.03 (1 set)	40.89 (8 sets)		45.87
	Simplex - Average	9.9	24.4	40.7	44.8	45.9
	Duplex - Adobe Reader	13.50	17.78 (1 set)	30.27 (6 sets)		37.25
	Duplex - Word	13.15	18.25 (1 set)	30.72 (6 sets)		37.29
	Duplex - Excel	13.38	17.94 (1 set)	30.95 (6 sets)		37.23
	Duplex - Average	13.4	17.9	30.6		37.2

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters	
Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 -3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCSHR ATA
I/O Subsystem	Builtin
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - A4

HP LaserJet Enterprise M506 Series

Printing device and settings

Test Start Date and Time	6/17/2015 21:53
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Temperature and Humidity	74 degF / 23 degC, 34 %rH
Voltage	110V
Test End Date and Time	6/30/2015 15:47

Item	Value	
Mode and Setting	Driver Version	Release15106_504-231
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	Default
	Duplex B&W Settings	Default
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Ultra White / HP Office

Summary Report: A4

Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	10.3	43.3
	Duplex	13.6	35.5

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: A4

	Office Category Test	FSOT (secs)	EFTP (ipm)			ESAT (ipm)
		1 set only (1 set)	1 set only (1 set)	1 set + 30sec (# of sets)	1 set + 4min (# of sets)	1 set + 30sec
Colour Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode <small>(optional for color device)</small>	Simplex - Adobe Reader	10.94	21.93 (1 set)	37.41 (7 sets)	42.41 (48 sets)	43.38
	Simplex - Word	9.79	24.51 (1 set)	37.94 (7 sets)		43.40
	Simplex - Excel	9.88	24.26 (1 set)	38.31 (7 sets)		43.30
	Simplex - Average	10.3	23.5	37.8	42.4	43.3
	Duplex - Adobe Reader	14.42	16.63 (1 set)	28.66 (6 sets)		35.60
	Duplex - Word	13.27	18.08 (1 set)	29.15 (6 sets)		35.54
	Duplex - Excel	13.01	18.45 (1 set)	29.20 (6 sets)		35.56
	Duplex - Average	13.6	17.7	29.0		35.5

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters

Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 - 3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCSHR ATA
I/O Subsystem	Builtin
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 24734 Printing Productivity Report: Office Category

Feature Performance Full Report - 'Office Feature Performance Test - A5

HP LaserJet Enterprise M506 Series

Printing device and settings	
Test Start Date and Time	6/17/2015 21:53
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Temperature and Humidity	74 degF / 23 degC, 34 %RH
Voltage	110V
Test End Date and Time	6/30/2015 15:47

Item	Value	
Mode and Setting	Driver Version	Release15106_504-231
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	Default
	Duplex B&W Settings	Default
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Ultra White / HP Office

ISO Print Productivity Report: Feature Performance Test Summary

Printing Modes (Feature Adobe Reader - Office test file)		Feature Performance Ratio	
		A5	
		FSOT (base)	ESAT (feature)
		FSOT (feature)	ESAT (base)
A5 Landscape Feed - Colour	Simplex		
A5 Portrait Feed - Colour	Simplex		
A5 Landscape Feed - B/W	Simplex	131%	151%
A5 Portrait Feed - B/W	Simplex		

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) Test conducted with 8-paper Office Feature Performance file.
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.

Feature Performance Full Report - Feature Printing Mode: 'Office' Feature Performance Test

Printing Modes Feature Adobe Reader - Office test file (8-page)	Base Printing Mode		Feature Performance			
			A5			
	FSOT Base	ESAT Base	1 set FSOT (secs)	1 set + 30 sec ESAT (ipm)	FSOT (base) FSOT (feature)	ESAT (feature) ESAT (base)
Simplex A5 Landscape Feed - Colour						
Simplex A5 Portrait Feed - Colour						
Simplex A5 Landscape Feed - B/W	16.86	43.41	12.79	66.0	131%	151%
Simplex A5 Portrait Feed - B/W	16.86	43.41				

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) Test conducted with 8-paper Office Feature Performance file.
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aCSHR ATA
	I/O Subsystem	BuiltIn
	USB Subsystem	USB 2.0/3.0
I/O	TCP/IP	TCP/IP 10/1000
Software	Operating System	Windows 7 64 Bit
	Printing Applications	Microsoft Office 2010
	Microsoft Office	Office 2010
	Adobe Reader	10
	Test files and location	Office category files, hard drive

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - LETTER

Printing device and settings	
Test Start Date and Time	6/17/2015 21:53
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Configuration (options)	Default
Controller	1.116
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	72 degF / 22 degC, 34.7 %rH
Voltage	110V
Test End Date and Time	6/30/2015 15:47

Mode and Setting	Item	Value
Mode and Setting	PDL and driver version	Release15106_504-231
	Print Quality mode	default
	B&W settings	default
	Paper feed orientation	Short Edge
Paper	Paper type setting	default
	Paper feeding	Standard cassette
	Paper exit	Standard exit tray
Paper Path	Output orientation	default (face up or face down)

ISO First Page Out Time Summary Report: Office Category

Summary Report: Letter		FPOT from Ready (seconds)
B&W	Simplex	5.86
	Duplex	9.99

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printersclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.

ISO First Page Out Time Report: Office Category

Detailed Report: LETTER						
		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Color Mode	FPOT from Ready - Simplex					
	FPOT from Ready - Duplex					
	FPOT from Sleep - Simplex			N/A		
	Recovery Time					
	FPOT from Off - Simplex					
	Warm-up Time					
B&W Mode	FPOT from Ready - Simplex	5.61	5.68	6.26	5.86	21 Seconds
	FPOT from Ready - Duplex	9.69	9.80	10.47	9.99	21 Seconds
	FPOT from Sleep - Simplex			7.97		60 Minutes
	Recovery Time			1.7		
	FPOT from Off - Simplex			89.58		
	Warm-up Time			83.32		

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printersclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.
 - 6) Details for FPOT from Sleep are shown below.

HP Data Table

Detailed Report: LETTER							
		FPOT Avg (secs)	FPOT (secs) Iteration 1	FPOT (secs) Iteration 2	FPOT (secs) Iteration 3	Application	Delay Time
Color Mode	FPOT from Sleep	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep (60 minutes) HP/Non ISO Test	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep	7.97	7.97	7.97	N/A	Adobe Reader	60 Minutes
B&W Mode	FPOT from Sleep (60 minutes) HP/Non ISO Test	7.97	7.97	7.97	N/A	Adobe Reader	60 Minutes

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) DLP includes detailed iterations as data measurements may vary run to run.

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aCSHR ATA
	I/O Subsystem	Builtin
	USB Subsystem	USB 2.0/3.0
Printing Device Connection	TCP/IP	10/1000
	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
Software	Printing Applications	Microsoft Office 2010 SP2
	Adobe Reader	Adobe Reader 10.1.4
	Print Driver	Release15106_504-231

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - A4

Printing device and settings	
Test Start Date and Time	6/17/2015 21:53
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Configuration (options)	Default
Controller	1.116
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	72 degF / 22 degC, 34.7 %rH
Voltage	110V
Test End Date and Time	6/30/2015 15:47

Mode and Setting	Item	Value
Mode and Setting	PDL and driver version	Release15106_504-231
	Print Quality mode	default
	B&W settings	default
Paper	Paper feed orientation	Short Edge
	Paper type setting	default
Paper Path	Paper feeding	Standard cassette
	Paper exit	Standard exit tray
	Output orientation	default (face up or face down)

ISO First Page Out Time Summary Report: Office Category

Summary Report: A4		
FPOT from Ready (seconds)		
B&W	Simplex	5.91
	Duplex	10.55

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.
- 5) Page counts were collected after completion of the tests.

ISO First Page Out Time Report: Office Category

Detailed Report: A4						
		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Color Mode	FPOT from Ready - Simplex					
	FPOT from Ready - Duplex					
	FPOT from Sleep - Simplex			N/A		
	Recovery Time					
	FPOT from Off - Simplex					
B&W Mode	Warm-up Time					
	FPOT from Ready - Simplex	5.63	5.73	6.35	5.91	21 Seconds
	FPOT from Ready - Duplex	10.20	10.29	11.14	10.55	21 Seconds
	FPOT from Sleep - Simplex			8.11		60 Minutes
	Recovery Time			1.8		
B&W Mode	FPOT from Off - Simplex			89.25		
	Warm-up Time			82.90		

Notes

- 1) All printing device and driver settings were default mode.
- 2) For the B/W results, the print driver was set to "print in B/W".
- 3) For more information see <http://www.hp.com/go/printerclaims>.
- 4) Port monitor not configured to follow device if the IP address changes.
- 5) Page counts were collected after completion of the tests.
- 6) Details for FPOT from Sleep are shown below.

HP Data Table

Detailed Report: A4							
		FPOT Avg (secs)	FPOT (secs) Iteration 1	FPOT (secs) Iteration 2	FPOT (secs) Iteration 3	Application	Delay Time
Color Mode	FPOT from Sleep	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep (60 minutes) HP/Non ISO Test	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep	8.11	8.09	8.12	N/A	Adobe Reader	60 Minutes
B&W Mode	FPOT from Sleep (60 minutes) HP/Non ISO Test	8.11	8.09	8.12	N/A	Adobe Reader	60 Minutes

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) DLP includes detailed iterations as data measurements may vary run to run.

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aCSHR ATA
	I/O Subsystem	Builtin
	USB Subsystem	USB 2.0/3.0
Printing Device Connection	TCP/IP	10/1000
Software	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
	Printing Applications	Microsoft Office 2010 SP2
	Print Driver	Adobe Reader 10.1.4 Release15106_504-231

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - LETTER

HP LaserJet Enterprise M506 Series

Printing device and settings	
Test Start Date and Time	6/26/2015 1:13
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Temperature and Humidity	74 degF / 23 degC, 44 %RH
Voltage	100V
Test End Date and Time	9/11/2015 18:16

Item	Value	
Mode and Setting	Driver Version	Release15106_504-231
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	Default
	Duplex B&W Settings	Default
	Setting N set count	Application
	Collating function	Activated (application)
Paper Path	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
	Duplexing Unit (Yes/No)	Yes
Paper	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Ultra White / HP Office

Summary Report: Letter			
Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	15.1	45.8
	Duplex	18.6	37.3

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: LETTER						
	Office Category Test	FSOT (secs) 1 set only (1 set)	EFTP (ipm)			ESAT (ipm) 1 set + 30sec
			1 set only (1 set)	1 set + 30sec (# of sets)	1 set + 4min (# of sets)	
Color Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode (optional for color device)	Simplex - Adobe Reader	15.36	15.62 (1 set)	36.90 (8 sets)	44.07 (50 sets)	45.93
	Simplex - Word	15.00	15.99 (1 set)	37.19 (8 sets)		45.88
	Simplex - Excel	14.91	16.09 (1 set)	37.24 (8 sets)		45.83
	Simplex - Average	15.1	15.9	37.1	44.0	45.8
	Duplex - Adobe Reader	18.87	12.72 (1 set)	27.89 (6 sets)		37.26
	Duplex - Word	18.29	13.12 (1 set)	28.33 (6 sets)		37.38
	Duplex - Excel	18.37	13.06 (1 set)	28.27 (6 sets)		37.36
	Duplex - Average	18.6	12.9	28.1		37.3

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters	
Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 -3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCSHR ATA
I/O Subsystem	Builtin
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 24734 Printing Productivity Report: Office Category

Full Detailed Test Report - A4

HP LaserJet Enterprise M506 Series

Printing device and settings	
Test Start Date and Time	6/26/2015 1:13
Tester	JB
Machine name/model	HP LaserJet Enterprise M506 Series
Colour or B&W	B&W
FW Version	2305090_000460
Temperature and Humidity	74 degF / 23 degC, 44 %RH
Voltage	100V
Test End Date and Time	9/11/2015 18:16

Item	Value	
Mode and Setting	Driver Version	Release15106_504-231
	Media/Quality Setting	Default / Default
	Simplex B&W Settings	Default
	Duplex B&W Settings	Default
	Setting N set count	Application
Paper Path	Collating function	Activated (application)
	Paper Sending Direction	Default
	Paper Size Setting	Default
	Paper Feeding	Tray 2
	Paper Exit	Standard Exit Tray
	Output Orientation	Default (face down)
Paper	Duplexing Unit (Yes/No)	Yes
	Paper Manufacturer	HP / Xerox
	Paper Weight	20lb / 75 g/m2
	Paper Size	Letter / A4
	Paper type/name	HP Multipurpose Ultra White / HP Office

Summary Report: A4			
Office Category Test for B&W Device		FSOT (seconds)	ESAT (ipm)
B&W	Simplex	16.0	43.5
	Duplex	18.9	35.7

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Detailed Report: A4						
	Office Category Test	FSOT (secs)	EFTP (ipm)			ESAT (ipm)
			1 set only (1 set)	1 set only (1 set)	1 set + 30sec (# of sets)	
Colour Mode	Simplex - Adobe Reader		(1 set)			
	Simplex - Word		(1 set)			
	Simplex - Excel		(1 set)			
	Simplex - Average					
	Duplex - Adobe Reader	N/A	N/A	N/A		N/A
	Duplex - Word	N/A	N/A	N/A		N/A
	Duplex - Excel	N/A	N/A	N/A		N/A
	Duplex - Average	N/A	N/A	N/A		N/A
B&W mode (optional for color device)	Simplex - Adobe Reader	15.88	15.10 (1 set)	34.20 (7 sets)	41.36 (48 sets)	43.39
	Simplex - Word	16.64	14.43 (1 set)	33.90 (7 sets)		43.75
	Simplex - Excel	15.40	15.58 (1 set)	34.58 (7 sets)		43.39
	Simplex - Average	16.0	15.0	34.2	41.3	43.5
	Duplex - Adobe Reader	19.38	12.38 (1 set)	26.76 (6 sets)		35.62
	Duplex - Word	18.53	12.95 (1 set)	27.31 (6 sets)		35.74
	Duplex - Excel	18.64	12.87 (1 set)	27.29 (6 sets)		35.84
	Duplex - Average	18.9	12.7	27.1		35.7

Notes
 1) All printing device and driver settings were default mode.
 2) For the B/W results, the print driver was set to "print in B/W".
 3) For more information see <http://www.hp.com/go/printerclaims>.
 4) Port monitor not configured to follow device if the IP address changes.

Test System Parameters	
Item	Value
Computer	HP Compaq Elite 8300 Small Form Factor
Processor	Intel Core i7 -3770, 3.4 GHz
System Chip Set	Intel C216 Chipset Family SMBus Host Controller
System Board	system devices, default system BIOS
System Memory	4 GB
Hard Drive Subsystem	Standard disk drive (Seagate)
Video Subsystem	AMD Radeon HD 6350
Optical Drive	HP DVD A DH16aCSHR ATA
I/O Subsystem	Builtin
USB Subsystem	USB 2.0/3.0
TCP/IP	TCP/IP 10/1000
Operating System	Windows 7 64 Bit
Printing Applications	Microsoft Office 2010
Microsoft Office	Office 2010
Adobe Reader	10
Test files and location	Office category files, hard drive

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - LETTER

HP LaserJet M506

Printing device and settings	
Test Start Date and Time	6/26/2015 1:13
Tester	JB
Machine name/model	HP LaserJet M506
Colour or B&W	B&W
FW Version	2305090_000460
Configuration (options)	Default
Controller	1.116
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	78 degF / 26 degC 28.3 %rH
Voltage	100V
Test End Date and Time	9/11/2015 18:16

Mode and Setting	Item	Value
Mode and Setting	PDL and driver version	Release15106_504-231
	Print Quality mode	default
	B&W settings	default
	Paper feed orientation	Short Edge
Paper	Paper type setting	default
	Paper feeding	Standard cassette
	Paper exit	Standard exit tray
Paper Path	Output orientation	default (face up or face down)

ISO First Page Out Time Summary Report: Office Category

Summary Report: Letter		FPOT from Ready (seconds)
B&W	Simplex	11.30
	Duplex	15.67

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.

ISO First Page Out Time Report: Office Category

Detailed Report: LETTER						
		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Color Mode	FPOT from Ready - Simplex					
	FPOT from Ready - Duplex					
	FPOT from Sleep - Simplex			N/A		
	Recovery Time					
	FPOT from Off - Simplex					
	Warm-up Time					
B&W Mode	FPOT from Ready - Simplex	11.05	11.19	11.63	11.30	21 Seconds
	FPOT from Ready - Duplex	15.42	15.53	16.04	15.67	21 Seconds
	FPOT from Sleep - Simplex			13.28		60 Minutes
	Recovery Time			1.7		
	FPOT from Off - Simplex			91.23		
	Warm-up Time			79.61		

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.
 - 6) Details for FPOT from Sleep are shown below.

HP Data Table

Detailed Report: LETTER							
		FPOT Avg (secs)	FPOT (secs) Iteration 1	FPOT (secs) Iteration 2	FPOT (secs) Iteration 3	Application	Delay Time
Color Mode	FPOT from Sleep	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep (60 minutes)	N/A	N/A	N/A	N/A	Adobe Reader	
	HP/Non ISO Test	N/A	N/A	N/A	N/A	Adobe Reader	
B&W Mode	FPOT from Sleep	13.28	13.51	13.05	N/A	Adobe Reader	60 Minutes
	FPOT from Sleep (60 minutes)	13.28	13.51	13.05	N/A	Adobe Reader	60 Minutes
	HP/Non ISO Test	13.28	13.51	13.05	N/A	Adobe Reader	60 Minutes

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) DLP includes detailed iterations as data measurements may vary run to run.

Test System Parameters		
Item	Value	
Test System	Computer	HP Compaq Elite 8300 Small Form Factor
	Processor	Intel Core i7 -3770, 3.4 GHz
	System Chip Set	Intel C216 Chipset Family SMBus Host Controller
	System Board	system devices, default system BIOS
	System Memory	4 GB
	Hard Drive Subsystem	Standard disk drive (Seagate)
	Video Subsystem	AMD Radeon HD 6350
	Optical Drive	HP DVD A DH16aCSHR ATA
	I/O Subsystem	Built-in
	USB Subsystem	USB 2.0/3.0
Printing Device Connection	TCP/IP	10/1000
	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
Software	Printing Applications	Microsoft Office 2010 SP2
	Adobe Reader	Adobe Reader 10.1.4
	Print Driver	Release15106_504-231

ISO/IEC 17629 First Print Out Time Report: Office Category

Full Detailed Test Report - A4

HP LaserJet M506

Printing device and settings	
Test Start Date and Time	6/26/2015 1:13
Tester	JB
Machine name/model	HP LaserJet M506
Colour or B&W	B&W
FW Version	2305090_000460
Configuration (options)	Default
Controller	1.116
Printing device page count	Not Specified
Printing supplies page count	Not Specified
Temperature and Humidity	78 degF / 26 degC 28.3 %rH
Voltage	100V
Test End Date and Time	9/11/2015 18:16

Mode and Setting	Item	Value
Mode and Setting	PDL and driver version	Release15106_504-231
	Print Quality mode	default
	B&W settings	default
Paper	Paper feed orientation	Short Edge
	Paper type setting	default
Paper Path	Paper feeding	Standard cassette
	Paper exit	Standard exit tray
	Output orientation	default (face up or face down)

ISO First Page Out Time Summary Report: Office Category

Summary Report: A4

FPOT from Ready (seconds)		
B&W	Simplex	11.41
	Duplex	15.82

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.

ISO First Page Out Time Report: Office Category

Detailed Report: A4

		Word (seconds)	Excel (seconds)	Adobe Reader (seconds)	Average (seconds)	Delay Time
Color Mode	FPOT from Ready - Simplex					
	FPOT from Ready - Duplex					
	FPOT from Sleep - Simplex			N/A		
	Recovery Time					
	FPOT from Off - Simplex					
	Warm-up Time					
B&W Mode	FPOT from Ready - Simplex	11.16	11.29	11.77	11.41	21 Seconds
	FPOT from Ready - Duplex	15.59	15.69	16.16	15.82	21 Seconds
	FPOT from Sleep - Simplex			13.63		60 Minutes
	Recovery Time			1.9		
	FPOT from Off - Simplex			92.17		
	Warm-up Time			80.40		

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) For more information see <http://www.hp.com/go/printerclaims>.
 - 4) Port monitor not configured to follow device if the IP address changes.
 - 5) Page counts were collected after completion of the tests.
 - 6) Details for FPOT from Sleep are shown below.

HP Data Table

Detailed Report: A4

		FPOT Avg (secs)	FPOT (secs) Iteration 1	FPOT (secs) Iteration 2	FPOT (secs) Iteration 3	Application	Delay Time
Color Mode	FPOT from Sleep	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep (60 minutes) HP/Non ISO Test	N/A	N/A	N/A	N/A	Adobe Reader	
	FPOT from Sleep	13.63	13.61	13.65	N/A	Adobe Reader	60 Minutes
B&W Mode	FPOT from Sleep (60 minutes) HP/Non ISO Test	13.63	13.61	13.65	N/A	Adobe Reader	60 Minutes

- Notes
- 1) All printing device and driver settings were default mode.
 - 2) For the B/W results, the print driver was set to "print in B/W".
 - 3) DLP includes detailed iterations as data measurements may vary run to run.

Test System Parameters

Item	Value	
Computer	HP Compaq Elite 8300 Small Form Factor	
Processor	Intel Core i7 -3770, 3.4 GHz	
System Chip Set	Intel C216 Chipset Family SMBus Host Controller	
System Board	system devices, default system BIOS	
System Memory	4 GB	
Hard Drive Subsystem	Standard disk drive (Seagate)	
Video Subsystem	AMD Radeon HD 6350	
Optical Drive	HP DVD A DH16aCSHR ATA	
I/O Subsystem	Builtin	
USB Subsystem	USB 2.0/3.0	
Printing Device Connection	TCP/IP	
Software	Operating System	Windows 7 Business/Ultimate, 64 bit, Build 7601, SP 1
	Printing Applications	Microsoft Office 2010 SP2
	Print Driver	Adobe Reader 10.1.4 Release15106_504-231